

说明书 尺寸:120x90mm 装订:骑马钉
128g双铜纸4色双面印刷

封底

封面



KEYS FUNCTION DISTRIBUTION:

DPI value: 600/1600/3400/5200/8000/16000DPI (which can be set)
Default lamp light DPI first level/red, second level/green, three level/purple, four level/blue, five level/yellow, six level/cyan.

6 kinds of RGB light effect:
1. Neon mode; 2. Breathing mode; 3. Flash mode; 4. Lightshow mode; 5. Ambilight mode; 6. LED OFF

The RGB light mode can be adjusted by "forward key + middle key".
Note: In wired and 2.4G mode, the RGB lights will turn off briefly when you move the mouse or click any button, and turn on when you don't move the mouse; in wireless mode, the RGB lights will turn off briefly when you move the mouse, and turn on when you don't move the mouse.

Mode switching operator:
Wired mode: plug in the Type-C data cable can be used.
2.4G mode: unplug the cable, turn on the power switch, press the mode key (bottom key) green light off, for 2.4G mode, plug in the receiver to use directly. (Forced to code while pressing the left middle right key for 3 seconds green light flashing plug in the receiver lights off pairing success. Note: the factory mouse has been and 2.4G receiver code, no need to pair code.)
Wireless mode: unplug the cable, turn on the power switch, press the mode key (bottom key) blue light slow flashing, enter the wireless mode, long press the left middle right button for about 3 seconds blue light fast flashing that is to enter the wireless pairing, open wireless on the computer and search for wireless devices see MS963WB wireless devices on the wireless connection, the light is off that the wireless connection is successful.

Charging indicator:
Red light slow flashing for low voltage alarm, blue light is always on when charging, blue light is off when full.

1. Left click: left click function
2. Right click: right click function
3. Wheel click: wheel click function
4. Previous click: back to previous page
5. Next click: enter to next page
6. DPI+: switch to higher DPI value, without loop switch
7. DPI-: switch to lower DPI value, without loop switch
8. Single comb: customize Ctrl, Shift, Alt, Win and any of the keyboard buttons to combine button functions
9. Macro settings: Display the set macro list, and select the set macro at will
10. Base: include Close windows, Lock PC, Show Desktop, Left click, Right click, Wheel click, Previous/mouse back function, Next/mouse forward function, Player, Play/Pause, Stop, Previous, Next, Volume, Mute, DPI+, Reset/Off functions
11. Disable key: to set bottom has no function
12. Polling rate: with 125/250/500/1000Hz to choose
13. Pointer accuracy: to adjust the movement speed of mouse
14. Scroll speed: to adjust the scroll wheel speed of mouse
15. Firing speed: to adjust the double-click speed of mouse
16. Export the current configuration: store the contents that have been set to your computer.
17. Import the configuration file: load the existing documents from the computer.
18. Reset: Set the mouse to the factory default
19. Apply: write the settings to mouse

For more functions, please enter "<http://www.havit.hk/downloads/>" to download the driver.

Main interface and functions description:

Macro definition
Macro management can record any keys of keyboard, the time of keys reaction and the number of keys cycles.

- Click [Create] to create a new file, such as a, b, c...
- Select whether to increase the delay and the times of cycles
- Click [Start recording] and start recording any keys of keyboard. The keys you recorded will display in the macro edit box
- After the recording, click "stop recording"
- To revise the recording content, please make the following changes in the macro options:
Choose to insert the event; insert relevant content in the selected location
Delete: Delete the selected content
Modify/Modify the delay value and input button again
- After recording is completed, just exit the macro recording interface, no need to click the confirmation keys
- Execute a macro, such as the mouse button @ key set to "macro functions", after recording is complete, press the mouse/key to play the recorded content

DPI settings
1. Six groups DPI: gear 1 / gear 2 / stalls 3 / stalls 4 / stalls 5 / stalls 6, check the selections
2. DPI setting: set the 6 groups of DPI value, adjust within the range of 600 - 8000DPI

产品名称:	MS963WB说明书
材质:	128g双铜
装订方式:	骑马钉
尺寸:	120*90(mm)
设计人:	设计部——何筱杰
定稿日期:	2024. 4. 7

Lighting settings
6 kinds of light effect: Neon mode--- Breathing mode--- Flash mode--- Lightshow mode--- Ambilight mode--- LED OFF

Uninstall
Open the control panel and open the "Add or Remove Programs" window, find "MS963WB Gaming Mouse" and click "Delete" to complete the uninstall program.

www.havitmart.com